

RACK-MEDIA16

Features

- Support 16 slots for FOC/FOCM series Media Converters
- 19-inch Rack Mount, 2U height
- 2 Slide-in Hot-swappable power supply system
- 3 fans
- LED indication for Primary (Power A) and Back (Power B) power supplies
- Plug & Play Operation
- Redundant and load sharing power supply system

Description

RACK-MEDIA16, Universal Media Converter Rack, provides 16 slots for any combination of FOC or FOCM Media Converters. Up to sixteen media converters can be powered by the Converter rack without the requirement of external power supplies. The unit features a redundant power supply system with automatic power load sharing to ensure proper operation even in case of a power supply problem.



More over, to acquire a convenient maintenance, 2 hot-swappable powers can be changed while **RACK-MEDIA16** is working. All above user-friendly designs make **RACK-MEDIA16** in a shape of high performance and reliability. **RACK-MEDIA16** can be used as a table top unit or installed into a 19-inch rack by using 19-inch brackets shipped together with the unit.

Specifications

Interface

Number of Module Slot: 16
Number of Power Slot: 2
Number of fixed Fan: 3

LED

Power A - Power B

Power

Slide in Power module
2 slots for redundancy
Hot-Swappable
AC version
Vac 110V or 240V - DC 5V
Power Consumption: 9.5 W (Empty Loading)
DC version
Vdc 48V +/- 5%

Typical Operation Temperature

Operation: 0°~50°C
Storage Temperature: -20°~60°C
Humidity: 5%~90% non-condensing

Case material

Iron / Steel, Plastic

Dimension and Weight

440 x 385x 88 mm (WxDxH)
Shipping Weight 10.8KG

Emission/Safety:

FCC Class A
CE

Order Information

RACK-MEDIA16N

Rack 19" 2U for redundancy power and FAN for 16 FOC-xxxx delivered without power module

RACK-MEDIA-AC

AC power module for RACK-MEDIA16N maxi 2

RACK-MEDIA-DC

DC 48V power module for RACK-MEDIA16N maxi 2

RACK-MEDIA16N-2AC

Rack 19" 2U with redundancy power included and 3 FAN for 16 FOC/FOCM



Rue de l'Ormette
28410 Abondant
France

Tel. : +33 237.628.790
Fax : +33 237.628.801
Email: trans@cxr.fr

Join us on the WEB :

www.cxr.anderson-jacobson.com

The information contained in this document are provided without warranty and do not constitute a contractual document. In order to improve its products, CXR reserves its right to modify without notice any part of this document.