

RACK-MEDIA16S

Features

- Support 16 slots for FOC series Media Converters
- 19-inch Rack Mount, 2U height
- 3 Hot-swappable fans
- LED indication for Power supply
- Plug & Play Operation
- Small Form Factor Converter Chassis
- With fixed AC Power Installed

Description

RACK-MEDIA16S, Universal Media Converter Rack, provides 16 slots for any combination of FOC Media Converters.

Up to sixteen media converters can be powered by the Converter rack without the requirement of external power supplies.

More over, to acquire a convenient maintenance, 3 Hot-swappable fans can be changed while **RACK-MEDIA16S** is working.

All above user-friendly designs make **RACK-MEDIA16S** in a shape of high performance and reliability. **RACK-MEDIA16S** can be used as a table top unit or installed into a 19-inch rack by using 19-inch brackets shipped together with the unit.



Specifications

Interface

Number of Module Slot: 16
Number of Fan: 3

LED

Power

Hot-Swappable

Fan

Power

Internal Power
AC 110V or 240V
Power Rated at 100W (Max)
DC 5V
Power Consumption: 9.5 W
(Empty Loading)

Typical Operation Temperature

Operation: 0°~50 °C
Storage Temperature: -20°~60 °C
Humidity: 5%~90% non-condensing

Case material

Iron / Steel, Plastic

Dimension and Weight

440 x 285x 88 mm (WxDxH)
Shipping Weight: 6.8KG

Emission/Safety:

FCC Class A

CE

*For further reports, please contact us for update



Rue de l'Ormette
28410 Abondant
France

Tel. : +33 237.628.790
Fax : +33 237.628.801
Email: trans@cxr.fr

Join us on the WEB :
www.cxr.anderson-jacobson.com

Order Information

RACK-MEDIA16S Rack 19" 2U with on AC power and 3 FAN for 16 FOC-xxxx

The information contained in this document are provided without warranty and do not constitute a contractual document. In order to improve its products, CXR reserves its right to modify without notice any part of this document.